



**J.B. Sound Industries Pty. Ltd.**

**43 Valencia St.**

**Greenacre 2190**

ACN: 002 346 278

**Manufacture & Consultancy:**

Custom Electronics, Printed Circuit Boards,  
Broadcast Equipment and Controlled Evacuation Systems

<http://www.jbsound.com.au>    [mail@jbsound.com.au](mailto:mail@jbsound.com.au)

**Ph. (02) 9750-4372, Int. +61-2-9750-4372**

**FAX. (02)9750-9406, Int. +61-2-9750-9406**

**E-RE8**

25mm wide Eurocard

E-RE8: is a Relay card with 8 independent, 2 change over relays, each relay has all contacts available on the 41612 rear connector.

The positive side of the coils are common and connected to the +24V rail via a diode to prevent reverse polarity connections, the negative side of the coils have 2 steering diodes, one to call an individual relay and one connected to an all call contact. There is a transient back EMF protection diode connected across each relay and a green LED in series with each coil.

The relays used are all socketed to allow easy maintenances, they are a long life type with dual, gold plated contacts for low level audio switching and switching capability of 1A up to 32V.

**Typical Uses:**

Studio changing controls, providing balanced left & right, delay controls and indicators,

Delay Switching including jingle insert,

Automatic backup program switching,

Matrix switching,

Monitor switching,

and any low level switching application required.



**Call J.B. Sound Industries Pty. Ltd to discuss your requirements.  
(02) 9750-4372, Fax & email available.**

