



J.B. Sound Industries Pty. Ltd.

43 Valencia St.

Greenacre 2190

ACN: 002 346 278

Manufacture & Consultancy:

Custom Electronics, Printed Circuit Boards,
Broadcast Equipment and Controlled Evacuation Systems

<http://www.jbsound.com.au> mail@jbsound.com.au

Ph. (02) 9750-4372, Int. +61-2-9750-4372

FAX. (02)9750-9406, Int. +61-2-9750-9406

T4 Case 104mm x 117mm, Mtg. 132mm Cts., Lugs 142mm.

T4 is an upgrade from our T3, the changes are from a 15VA transformer to a 30VA transformer and a larger range of output voltages are available. This provides a 15VA rating from each of the two outputs, either AC or DC.

AC or DC output are not available together and these are selected by an internal switch, and indicated on the outside of the case by an illuminated LED beside the active terminals. These LEDs are normally Green for DC and Red for AC, but may be in any available colour to your requirement.

The T4 supply is only available for 240V AC primary, a Varistor, transient Suppressor, is fitted and a 5mm x 20mm 500mA fuse.



Output from each pair of terminals is dependent on the model/voltage ordered and is available in the following single winding voltages:

6V AC	8.4V DC
7.5V AC	10.6V DC
9V AC	12.7V DC
12V AC	16.9V DC
15V AC	21.2V DC

The DC output is Capacitively filtered but not regulated.

Windings may be used separately or in series or parallel.

Typical Uses:

Powering of small projects ie.

DBA/2,

Remote Recording Limiters,

Many other small non Card Frame mounted modules.

Call J.B. Sound Industries Pty. Ltd to discuss your requirements.

(02) 9750-4372, Fax & email available.